

Feature

This device is Pb-Free, Halogen Free/BFR Free and RoHS compliant.

PNMT8N1 is composed by a transistor and a MOSFET



Transistor:

- Very low collector to emitter saturation voltage
- DC current gain >100
- 3A continuous collector current
- PNP epitaxial planar silicon transistor

MOSFET:

MOSFET Product Summary		
V _{DS} (V)	R _{DS(on)} (Ω)	I _D (mA)
20	0.3@ V _{GS} =4.0V	±300
	0.45@ V _{GS} =2.5V	
	0.6@ V _{GS} =1.8V	

- Transistor


Electrical characteristics per line@25°C (unless otherwise specified)

Parameter	Symbol	Conditions	Value	Units
Collector-Emitter Breakdown Voltage	V _{(BR)CEO}	I _C = -10mA	-30	V
Collector-Base Breakdown Voltage	V _{(BR)CBO}	I _C = -0.1mA	-40	V
Emitter -Base Breakdown Voltage	V _{(BR)EBO}	I _E = -0.1mA	-5	V
Collector Current	I _C		-3	A
Collector Peak Current	I _{CM}		-6	A
Base Current	I _B		-0.2	A
Base Peak Current	I _{BM}		-0.5	A
Total Dissipation @25°C	P _{tot}		2.5	W
Storage Temperature	T _{stg}		-65~150	°C
Operating Temperature	T _j		-40~125	°C
Junction-to-Ambient Thermal Resistance ⁽¹⁾	R _{θJA}		50	°C/ W

Note 1: Surface mounted on FR-4 Board using 1 square inch pad size, 1oz copper

Absolute maximum rating@25°C

Parameter	Symbol	Conditions	Min.	Typ.	Max.	Units
DC Current Gain	h_{FE}	$I_C=-100mA, V_{CE}=-2V$	200	-	-	-
		$I_C=-2A, V_{CE}=-2V$	100	-	-	
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$	$I_C=-0.1A, I_B=-10mA$	-	-	-25	mV
		$I_C=-1A, I_B=-20mA$	-	-	-210	
		$I_C=-1.5A, I_B=-50mA$	-	-	-230	
		$I_C=-2.5A, I_B=-150mA$	-	-	-300	
		$I_C=-3.5A, I_B=-350mA$	-	-	-350	
Base-Emitter Saturation Voltage	$V_{BE(sat)}$	$I_C=-1A, I_B=-0.05mA$	-	-	-1.1	V
Collector Cut-off Current ($I_E=0$)	I_{CBO}	$V_{CB}=-40V$	-	-	-0.1	μA
		$V_{CB}=-30V, T_C=125^\circ C$	-	-	-20	
Emitter Cut-off Current ($I_C=0$)	I_{EBO}	$V_{EB}=-5V$	-	-	-0.1	μA

➤ MOSFET

Electrical characteristics per line@25°C (unless otherwise specified)

Parameter	Symbol	Conditions	Min.	Typ.	Max.	Units
OFF CHARACTERISTICS						
Drain-Source Breakdown Voltage	BV_{DSS}	$I_D=1mA, V_{GS}=0V$	20	-	-	V
Zero Gate Voltage Drain Current	I_{DSS}	$V_{DS}=20V, V_{GS}=0V$	-	-	1	μA
Gate-Body Leakage Current	I_{GSS}	$V_{DS}=0V, V_{GS}=\pm 8V$	-	-	± 10	μA
Gate Threshold Voltage	$V_{GS(th)}$	$V_{DS}=10V, I_D=1mA$	0.5	-	1.1	V
Static Drain-Source On-Resistance	$R_{DS(on)}$	$V_{GS}=4.0V, I_D=300mA$	-	0.3	0.5	Ω
		$V_{GS}=2.5V, I_D=200mA$	-	0.45	0.7	Ω
		$V_{GS}=1.8V, I_D=150mA$	-	0.6	0.9	Ω
DYNAMIC PARAMETERS						
Input Capacitance	C_{ISS}	$V_{GS}=0V, V_{DS}=10V,$ $f=1MHz$	-	30	-	pF
Output Capacitance	C_{DSS}		-	13	-	pF
Reverse Transfer Capacitance	C_{RSS}		-	13	-	pF
SWITCHING PARAMETERS						
Turn-On Delay Time	$t_{d(on)}$	$V_{DD}=10V, V_{GS}=4.0V,$ $R_G=10\Omega, R_L=67\Omega$ $I_D=150mA$	-	7	-	ns
Turn-Off Delay Time	$t_{d(off)}$		-	23	-	ns

Absolute maximum rating@25°C

Rating		Symbol	Value	Units
Drain-Source Voltage		V_{DS}	20	V
Gate-Source Voltage		V_{GS}	± 8	V
Drain Current	Continuous	I_D	0.3	A
	Pulsed	I_D	0.6	A
Total Power Dissipation	$T_A=25^\circ C$	P_D	150	mW

Typical Characteristics




Fig1. Collector-emitter voltage V_{CE} (V)




Fig2. DC Current Gain




Fig 3. Collector-Emitter Saturation Voltage




Fig4. Base-Emitter Saturation Voltage




Fig 5. Switching Times Resistive Load




Fig 6. Switching Times Resistive Load




Fig 7. Output Characteristics




Fig 8. Transfer Characteristics




Fig 9. On-Resistance vs. Drain Current






Fig 10. Capacitance

Product dimension DFN3020-8L



Dim	Millimeters	
	MIN	MAX
A	0.55	0.65
A1	--	0.05
A3	0.20REF	
D	1.90	2.10
E	2.90	3.10
D1	0.30	0.50
E1	0.70	0.90
D2	1.70	1.90
D3	0.20	0.40
D4	0.20	0.40
D5	0.25	0.45
b	0.25	0.35
e	0.65TYP	
k	0.20MIN	
L	0.25	0.35




Unit:mm

Ordering information


Device	Package	Shipping
PNMT8N1	DFN3020-8L	3000 / Tape & Reel

Load with information



Unit:mm


IMPORTANT NOTICE

 and **Prisemi**[®] are registered trademarks of **Prisemi Electronics Co., Ltd** (Prisemi). Prisemi reserves the right to make changes without further notice to any products herein. Prisemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Prisemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in Prisemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Prisemi does not convey any license under its patent rights nor the rights of others. The products listed in this document are designed to be used with ordinary electronic equipment or devices, Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

Website: <http://www.prisemi.com>

For additional information, please contact your local Sales Representative.

©Copyright 2009, Prisemi Electronics

 **Prisemi**[®] is a registered trademark of Prisemi Electronics.

All rights are reserved.